

1800W Gasoline Generator



Product Features:

- Powerful 3 HP, 4 stroke air cooled OHV engine
- Electronic ignition
- Low oil shut-off with indicator light protects the engine
- Duplex Outlet: 120V/11.6 Amp. AC output
- Terminals: 12V, 8 Amp. DC output
- Easy start recoil starter
- AC and DC circuit breakers for safe operation
- Comes with DC cables and spark plug socket
- CSA and EPA approved

MODEL	KCG-1501GX
PEAK WATTAGE (STARTING)	1800W
RUNNING WATTAGE	1400W
AC OUTPUTS	2 x 120V / 11.6 Amp.
DC OUTPUT	12V (8 Amp.)
ENGINE (OHV)	3 HP
NO LOAD SPEED	3,600 RPM
DISPLACEMENT (CC)	98
FUEL	Unleaded gasoline
FUEL TANK (L)	7
OIL CAPACITY (L)	0.5
RUN TIME	9 hrs
NOISE LEVEL	66 dB(A)
ASSEMBLED DIMENSIONS (LxWxH) / WEIGHT	18-1/2" x 14" x 15-1/4" / 56 lbs
PACKAGE DIMENSIONS (LxWxH) / WEIGHT	19" x 14-1/2" x 15-1/2" / 59.5 lbs
UPC	7 72995 01681 5