

## 2500W Gasoline Digital Inverter Generator

### Product Features:

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Powerful 3 HP, 4 stroke air cooled OHV engine
- Carbon monoxide (CO DETECTOR™) safety system is designed to detect harmful levels of CO which accumulate within the generator work area and automatically shuts down the generator
- DC USB ports (A & C): 5V DC output for charging smartphones, tablets or any USB powered equipment
- DC Cigarette Lighter Socket: 12V/8 Amp. DC output
- AC Duplex Outlet: 120V/13.3 Amp. AC output
- Parallel connectivity between two inverter generators for combined output power (optional Parallel Cable Kit needed)
- Economical mode switch for improved fuel consumption
- Low oil shut-off, overload and power indicator lights
- Comes with spark plug socket and funnel
- CSA & EPA approved



<b>MODEL</b>	<b>KCG-2500i</b>
<b>PEAK WATTAGE (STARTING)</b>	2500W
<b>RUNNING WATTAGE</b>	1800W
<b>AC OUTPUT</b>	1 (2x 120V, 13.3A)
<b>DC OUTPUT</b>	12V (DC 8A)
<b>ENGINE (OHV)</b>	3 HP
<b>NO LOAD SPEED</b>	3,350 RPM
<b>DISPLACEMENT (CC)</b>	80
<b>FUEL</b>	Unleaded Gasoline
<b>FUEL TANK (L)</b>	4.2
<b>OIL CAPACITY (L)</b>	0.35
<b>RUN TIME</b>	6 - 8 hrs
<b>TOTAL HARMONIC DISTORTION (THD%)</b>	≤ 3%
<b>NOISE LEVEL</b>	64 dB(A)
<b>ASSEMBLED DIMENSIONS (LxWxH) / WEIGHT</b>	19-1/4" x 11-1/2" x 19" / 45 lbs
<b>PACKAGE DIMENSIONS (LxWxH) / WEIGHT</b>	20-3/4" x 13-3/16" x 20-1/8" / 50 lbs
<b>UPC</b>	7 72995 02120 8